

## ECE-320, Practice Quiz #1

Problems 1-3 assume we have a system modeled with the transfer function

$$H(s) = \frac{s+2}{(s+1)(s+3)(s+4)}$$

1) This system model has how many **zeros**?

- a) 0 b) 1 c) 2 d) 3

2) This system model has how many **poles**?

- a) 0 b) 1 c) 2 d) 3

3) How many terms will there be in the partial fraction expansion?

- a) 0 b) 1 c) 2 d) 3

4) How many terms will there be in the partial fraction expansion of  $H(s) = \frac{1}{s(s+1)^2}$ ?

- a) 0 b) 1 c) 2 d) 3

5) The **bandwidth** (3 dB point) of the system with transfer function  $H(s) = \frac{10}{s+10}$  is

- a) 10 Hz b) 1 Hz c) 10 radians/sec d) 1 radians/sec

6) The **bandwidth** (smallest 3 dB point) of the system with transfer function

$$H(s) = \frac{40}{(s+2)(s+20)} \text{ is}$$

- a) 2 Hz b) 20 Hz c) 2 radians/sec d) 20 radians/sec

For problems 7-9 assume we have a system modeled by the transfer function  $H(s)$ .

7) To determine the **impulse response** we should compute the inverse Laplace transform of

a)  $Y(s) = H(s)$     b)  $Y(s) = H(s)\frac{1}{s}$     c)  $Y(s) = H(s)\frac{1}{s^2}$     d)  $Y(s) = H(s)\frac{1}{s^3}$

8) To determine the **(unit) step response** we should compute the inverse Laplace transform of

a)  $Y(s) = H(s)$     b)  $Y(s) = H(s)\frac{1}{s}$     c)  $Y(s) = H(s)\frac{1}{s^2}$     d)  $Y(s) = H(s)\frac{1}{s^3}$

9) To determine the **(unit) ramp response** we should compute the inverse Laplace transform of

a)  $Y(s) = H(s)$     b)  $Y(s) = H(s)\frac{1}{s}$     c)  $Y(s) = H(s)\frac{1}{s^2}$     d)  $Y(s) = H(s)\frac{1}{s^3}$

10) For the transfer function

$$H(s) = \frac{1}{s(s+2)^2}$$

the corresponding impulse response  $h(t)$  is composed of which terms?

- a)  $t^2 e^{-2t}$
- b)  $t$  and  $te^{-2t}$
- c)  $1$  and  $te^{-2t}$
- d)  $te^{-2t}$
- e)  $1$ ,  $e^{-2t}$ , and  $te^{-2t}$

Problems 11 and 12 refer to the following transfer function  $H(s) = \frac{2s+1}{(s+1)^2+4}$

**11)** For this transfer function, the corresponding impulse response  $h(t)$  is composed of which terms?

- a)  $e^{-t} \cos(2t), e^{-t} \sin(2t)$       b)  $e^{-2t} \cos(t), e^{-2t} \sin(t)$   
 c)  $e^{-t} \cos(4t), e^{-t} \sin(4t)$       d)  $e^{-4t} \cos(t), e^{-4t} \sin(t)$

**12)** The **poles** of the transfer function are

- a)  $2 \pm j$                       b)  $-2 \pm j$   
 c)  $-1 \pm 2j$                     d)  $-1 \pm 4j$

**13)** An impulse response  $h(t)$  is composed of the terms  $1, t, e^{-t}$   
 A possible corresponding transfer function (for some constant value  $A$ ) is

- a)  $H(s) = \frac{A}{s(s+1)}$                       b)  $H(s) = \frac{A}{s^2(s+1)}$   
 c)  $H(s) = \frac{As}{(s+1)}$                       d)  $H(s) = \frac{A}{s(s+1)^2}$

**14)** In using partial fractions to go from the Laplace domain to the time domain for a transfer function with no pole/zero cancellations, the number of terms used in the partial fraction expansion is determined by

- a) the zeros of the transfer function      b) the poles of the transfer function

**15)** For the transfer function

$$H(s) = \frac{s+1}{(s+1)(s+2)^2}$$

The partial fraction expansion will be of the form

- a)  $H(s) = \left( \frac{A}{s+1} \right) \left( \frac{B}{s+2} \right) \left( \frac{C}{(s+2)^2} \right)$       b)  $H(s) = \frac{A}{s+1} + \frac{B}{s+2} + \frac{C}{(s+2)^2}$   
 c)  $H(s) = \frac{A}{s+1} + \frac{C}{(s+2)^2}$                       d)  $H(s) = \left( \frac{A}{s+1} \right) \left( \frac{C}{(s+2)^2} \right)$

*Answers: 1-b, 2-d, 3-d, 4-d, 5-c, 6-c,  
 7-a, 8-b, 9-c, 10-e,  
 11-a, 12-c, 13-b, 14-b, 15-b*