

ECE-320: Linear Control Systems
Homework 7

Due: **Thursday** January 30 at the beginning of class

1) (Easy) Show that $\sum_{l=-\infty}^{l=n} \delta(l) = u(n)$ and $\sum_{l=-\infty}^{l=n} \delta(l-k) = u(n-k)$

2) (Easy) For impulse response $h(n) = \delta(n) + 2\delta(n-2) + 3\delta(n-3)$ and input

$x(n) = \left(\frac{1}{2}\right)^{n-1} u(n-2)$, determine the output $y(n)$ (this should be easy).

3) For impulse response $h(n) = \left(\frac{1}{2}\right)^n u(n)$ and input $x(n) = u(n)$, show that the system output is

$$y(n) = 2 \left[1 - \left(\frac{1}{2}\right)^{n+1} \right] u(n)$$

a) by evaluating the convolution sum $y(n) = \sum_{k=-\infty}^{k=\infty} x(n-k)h(k)$

b) by evaluating the convolution sum $y(n) = \sum_{k=-\infty}^{k=\infty} x(k)h(n-k)$

Note that this is the unit step response of the system.

4) For impulse response $h(n) = \left(\frac{1}{3}\right)^{n-2} u(n-1)$ and input $x(n) = \left(\frac{1}{2}\right)^n u(n-1)$, show that the system

output is $y(n) = 9 \left[\left(\frac{1}{2}\right)^{n-1} - \left(\frac{1}{3}\right)^{n-1} \right] u(n-2)$ by evaluating the convolution sum

$$y(n) = \sum_{k=-\infty}^{\infty} x(n-k)h(k)$$

5) For impulse response $h(n) = \left(\frac{1}{2}\right)^{n-3} u(n-1)$ and input $x(n) = \left(\frac{1}{4}\right)^{n+1} u(n-2)$, show that the system

output is $y(n) = \left[\left(\frac{1}{2}\right)^n - \left(\frac{1}{4}\right)^{n-1} \right] u(n-3)$ by evaluating the convolution sum $y(n) = \sum_{k=-\infty}^{\infty} h(n-k)x(k)$

6) For impulse response $h(n) = \left(\frac{1}{3}\right)^{n+1} u(n-2)$ and input $x(n) = \left(\frac{1}{2}\right)^{n-2} u(n+1)$, show that the system output is $y(n) = \frac{16}{9} \left[\left(\frac{1}{2}\right)^n - \left(\frac{1}{3}\right)^n \right] u(n-1)$ by evaluating the convolution sum $y(n) = \sum_{k=-\infty}^{\infty} h(n-k)x(k)$

7) For $h(n) = \left(\frac{1}{a}\right)^n u(-n) + a^n u(n)$ with $|a| < 1$, using the two-sided z transform to show that

$$H(z) = \frac{1}{1-az} + \frac{1}{1-az^{-1}}$$

and the region of convergence is $|a| < |z| < \frac{1}{|a|}$.