

ECE-420: Discrete-Time Control Systems
Homework 2

Due: Friday September 20 at the beginning of class

1) For the z -transform

$$X(z) = \frac{3}{z-2}$$

a) Show that, by multiplying and dividing by z and then using partial fractions, the corresponding discrete-time sequence is

$$x(k) = -\frac{3}{2} \delta(k) + \frac{3}{2} 2^k u(k)$$

b) By starting with the z -transform

$$G(z) = \frac{3z}{z-2}$$

where $Y(z) = z^{-1}G(z)$ and the z -transform properties, show that

$$x(k) = 3 \cdot 2^{k-1} u(k-1)$$

2) For the following transfer functions, use **long division** to determine estimates of the first few terms of the impulse responses

a) $H(z) = \frac{z^3 + 2z^2 + 3z + 2}{z + 2}$

b) $H(z) = \frac{z^2 + 2z + 1}{z^3 + 3z}$

Answers: $h(n) = \delta(n+2) + 3\delta(n) - 4\delta(n-1) + 8\delta(n-2) - 16\delta(n-3) + \dots$

$h(n) = \delta(n-1) + 2\delta(n-2) - 2\delta(n-3) - 6\delta(n-4) + \dots$

3) For impulse response $h(n) = \left(\frac{1}{2}\right)^n u(n-2)$ and input $x(n) = \left(\frac{1}{3}\right)^n u(n-2)$, use z -transforms of the

input and impulse response to show the system output is $y(n) = \frac{1}{6} \left[\left(\frac{1}{2}\right)^{n-3} - \left(\frac{1}{3}\right)^{n-3} \right] u(n-3)$

Hint: Assume $Y(z) = z^{-3}G(z)$, determine $g(n)$ and then $y(n)$

4) For impulse response $h(n) = \left(\frac{1}{3}\right)^{n+1} u(n-1)$ and input $x(n) = \left(\frac{1}{2}\right)^{n-1} u(n-2)$, use z -transforms of the input and impulse response to show the system output is $y(n) = \frac{1}{3} \left[\left(\frac{1}{2}\right)^{n-2} - \left(\frac{1}{3}\right)^{n-2} \right] u(n-2)$

Hint: Assume $Y(z) = z^{-2}G(z)$, determine $g(n)$ and then $y(n)$

5) For impulse response $h(n) = \left(\frac{1}{2}\right)^{n-1} u(n)$ and input $x(n) = \left(\frac{1}{5}\right)^{n-2} u(n-3)$, use z -transforms of the input and impulse response to show the system output is $y(n) = \frac{4}{3} \left[\left(\frac{1}{2}\right)^{n-2} - \left(\frac{1}{5}\right)^{n-2} \right] u(n-2)$

Hint: Assume $Y(z) = z^{-2}G(z)$, determine $g(n)$ and then $y(n)$

6) In class we derived the relation ships

$$G(z) = \frac{rz[z \cos(\theta) - \gamma \cos(\beta - \theta)]}{z^2 - 2\gamma \cos(\beta)z + \gamma^2} = \frac{Az^2 + Bz}{z^2 + 2Cz + \gamma^2} \leftrightarrow g(n) = r\gamma^n \cos(\beta n + \theta)u(n)$$

with

$$\beta = \cos^{-1}\left(\frac{-C}{\gamma}\right), \theta = \tan^{-1}\left(\frac{CA - B}{A\sqrt{\gamma^2 - C^2}}\right), r = \sqrt{\frac{A^2\gamma^2 + B^2 - 2ABC}{\gamma^2 - C^2}}$$

a) Use the above formulas to find the impulse response $g(n)$ for $G(z) = \frac{z^2 + 0.5z}{z^2 + 0.2z + 0.125}$.

b) Compute $g(n)$ from part a for $n = 0, 1, 2, 3, 4$ and then perform long division to verify that your answer to a is correct for these terms

c) Determine the unit step response $y(n)$ for $G(z) = \frac{1}{z^2 + 0.1z + 4}$, by using the form

$$\frac{Y(z)}{z} = \frac{1}{(z-1)(z^2 + 0.1z + 4)} = \frac{\alpha_1}{z-1} + \frac{\alpha_2 z + \alpha_3}{z^2 + 0.1z + 4}$$

Hint: α_1 can be found using the cover-up method, α_2 can be found by multiplying both sides by z and letting $z \rightarrow \infty$, and α_3 can be found by substituting a convenient value for z , like $z = 0$.

d) Compute $y(n)$ from part c for $n = 0, 1, 2, 3, 4$ and then perform long division to verify that your answer to c is correct for these terms

7) Consider the following difference equation

$$x(k+2) - 4x(k+1) + 4x(k) = f(k)$$

Assume all initial conditions are zero.

- a) Determine the impulse response of the system, i.e., the response $x(k)$ when $f(k) = \delta(k)$.
- b) Determine $h(0)$, $h(1)$, $h(2)$, $h(3)$, and $h(4)$ from your answer to **a**. Compare this answer with the known values of $h(0)$ and $h(1)$. Using the difference equation compute $h(3)$ and $h(4)$ and compare these values to those in your solution (they should be the same!)
- c) Determine the step response of the system, i.e., the response $x(k)$ when $f(k) = u(k)$
- d) Determine $x(0)$, $x(1)$, $x(2)$, $x(3)$, and $x(4)$ from your answer to **c**. Compare this answer with the known values of $x(0)$ and $x(1)$. Using the difference equation compute $x(3)$ and $x(4)$ and compare these values to those in your solution.
- 8) Consider the difference equation

$$x(k+2) - 5x(k+1) + 6x(k) = f(k)$$

where $f(k) = u(k)$, a unit step. Assume $x(0) = 1$ and $x(1) = 1$.

- a) Determine the Zero Input Response (ZIR), $x_{ZIR}(k)$. This is the part of the solution $x(k)$ due to the initial conditions alone (assume the input is zero).
- b) Determine the Zero State Response (ZSR), $x_{ZSR}(k)$. This is the part of the solution $x(k)$ due to the input alone (assume all initial conditions are zero).
- c) Find the total response $x(k) = x_{ZIR}(k) + x_{ZSR}(k)$
- d) Find the transfer function and the impulse response.
- e) Determine $x(0)$, $x(1)$, $x(2)$, $x(3)$, and $x(4)$ from your answer to **c**. Compare this answer with the known values of $x(0)$ and $x(1)$. Using the difference equation compute $x(3)$ and $x(4)$ and compare these values to those in your solution.