

### ECE-320, Practice Quiz #8

1) Consider the following state variable model

$$\dot{q}(t) = \begin{bmatrix} 0 & 1 \\ 1 & 1 \end{bmatrix} q(t) + \begin{bmatrix} 0 \\ 2 \end{bmatrix} u(t)$$
$$y(t) = [3 \quad 0] q(t)$$

Assume state variable feedback of the form  $u(t) = G_{pf}r(t) - Kq(t)$  The closed loop transfer function for this system is which of the following?

- a)  $G(s) = \frac{-6G_{pf}}{s(s-1+2k_2)+2k_1-1}$     b)  $G(s) = \frac{6G_{pf}}{s(s-1+2k_2)+2k_1-1}$
- c)  $G(s) = \frac{6G_{pf}}{s(s-1+2k_2)-2k_1+1}$     d)  $G(s) = \frac{-6G_{pf}}{s(s-1+2k_2)-2k_1+1}$

2) Consider the following state variable model

$$\dot{q}(t) = \begin{bmatrix} -1 & 2 \\ 0 & 1 \end{bmatrix} q(t) + \begin{bmatrix} 1 \\ 0 \end{bmatrix} u(t)$$
$$y(t) = [1 \quad 0] q(t)$$

Assume state variable feedback of the form  $u(t) = G_{pf}r(t) - Kq(t)$  Is the closed loop transfer function for this system equal to

$$G(s) = \frac{G_{pf}}{s+1+k_1}$$

- a) yes    b) no

Problems 3-6 refer to a system with state variable feedback with the transfer function

$$G(s) = \frac{8G_{pf}}{s^2 + (k_1 + 12)s + (k_1 + k_2 + 20)}$$

3) Is this system *controllable*?

a) Yes b) No c) impossible to determine

4) What is the approximate bandwidth of the open loop system?

a) 2 Hz b) 2 rad/sec c)  $2\pi$  rad/sec d) 10 Hz

5) In order for the open loop system to have a zero steady state error for a unit step input, the value of the prefilter should be

a)  $G_{pf} = 1$  b)  $G_{pf} = \frac{2}{5}$  c)  $G_{pf} = \frac{5}{2}$  d) none of these

6) If we want to choose the feedback gains so the bandwidth of the system is 5 rad/sec and the second pole is 4 time further from the imaginary axis than the first pole (both are assumed to be real poles), then we should choose the gains to be

a)  $k_1 = 5, k_2 = 20$  b)  $k_1 = 25, k_2 = 100$  c)  $k_1 = 13, k_2 = 87$  d)  $k_1 = 13, k_2 = 67$  e) none of these

Problems 7-10 refer to a system with state variable feedback that has the following transfer function

$$G(s) = \frac{G_{pf}}{s^2 + (k_1 - 1)s + (k_2 + 2)}$$

7) Is the system controllable?

a) Yes b) No c) impossible to determine

8) In order for the open loop system to have a zero steady state error for a unit step input, the value of the prefilter should be

a)  $G_{pf} = 1$  b)  $G_{pf} = 2$  c)  $G_{pf} = -1$  d) none of these

9) Assume we use our state variable feedback to place both poles at -5. Then we should choose the gains to be

a)  $k_1 = 5, k_2 = 5$  b)  $k_1 = 10, k_2 = 25$  c)  $k_1 = 11, k_2 = 23$  d)  $k_1 = 9, k_2 = 27$  e) none of these

10) Assume we use our state variable feedback to place both poles at -5. If we want a zero steady state error for a unit step input, then the prefilter gain should be

a)  $G_{pf} = 1$  b)  $G_{pf} = 2$  c)  $G_{pf} = 5$  d)  $G_{pf} = 25$  e) none of these

**11)** A system with state variable feedback has the following transfer function

$$G(s) = \frac{G_{pf}}{(s - k_1 k_2)^2}$$

Is the system controllable?

a) Yes   b) No   c) impossible to determine

**12)** Consider a plant that is unstable but is a controllable system. Is it possible to use state variable feedback to make this system stable?

a) Yes   b) No

*Answers: 1-b, 2-a,  
3-a, 4-b, 5-c, 6-d, 7-a, 8-b, 9-c, 10-d,  
11-b, 12-a,*