ECE-205

Exam 3 Winter 2010-2011

Calculators and computers are not allowed. You must show your work to receive credit.

Problem 1	/30
Problem 2	/20
Problem 3	/20
Problem 4	/15
Problems 5-9	/15 (3 points each)
Total	


1) (30 points) For the following transfer functions, determine the <u>unit step response</u> of the system. *Do not forget any necessary unit step functions*.

a)
$$H(s) = \frac{1}{(s+1)(s+2)}$$

b)
$$H(s) = \frac{e^{-3s}}{(s+1)^2}$$


c)
$$H(s) = \frac{13}{s^2 + 4s + 13}$$

2) (20 points) Consider the following simple feedback control block diagram. The plant, the thing we want to control, has the transfer function $G_p(s) = \frac{5}{s+2}$




- a) Determine the settling time of the plant alone (assuming there is no feedback)
- **b)** For a proportional controller, $G_c(s) = k_p$, determine the closed loop transfer function $G_0(s)$ and then
 - i) the settling time, in terms of k_p
 - ii) the steady state error for a unit step, in terms of k_p
- c) For and integral controller, $G_c(s) = \frac{k_i}{s}$, determine the closed loop transfer function $G_0(s)$ and the steady state error for a unit step in terms of k_i

3) (**20 points**) For the following circuit determine the <u>transfer function</u> and the corresponding <u>impulse response</u>.




4) (15 points) For the following signal flow diagram



Determine the system transfer function using Mason's gain rule. You must clearly indicate all of the paths, the loops, the determinant and the cofactors, but <u>you do not need to simplify your final</u> <u>answer</u> (it can be written in terms of the P_i , L_i , and Δ_i)

Name _____ Mailbox _____

Problems 5 and 6 refer to the unit step response of a system, shown below



- 5) The best estimate of the steady state error for a unit step input is
- a) 0.50 b) 0.25 c) -0.25 d) 0.0 e) impossible to determine

6) The best estimate of the **percent overshoot** is a) 20% b) 50% c) 25% d) 150%

7) How many of the following transfer functions represents (asymptotically) stable systems?

$$G_a(s) = \frac{s+1}{s-1}$$

$$G_b(s) = \frac{1}{s(s+1)}$$
 $G_c(s) = \frac{s}{s^2 - 1}$


$$G_c(s) = \frac{s}{s^2 - 1}$$

$$G_d(s) = \frac{s+1}{(s+1+j)(s+1-j)}$$

$$G_e(s) = \frac{(s-1-j)(s-1+j)}{s}$$

$$G_d(s) = \frac{s+1}{(s+1+j)(s+1-j)} \quad G_e(s) = \frac{(s-1-j)(s-1+j)}{s} \quad G_f(s) = \frac{(s-1-j)(s-1+j)}{(s+1-j)(s+1+j)}$$

8) For the unit ramp response of a system shown below, the best estimate of the steady state error is



9) For a plant with transfer function $G_p(s) = \frac{5}{(s+4)(s+2)}$ The (2%) settling time for this plant is

- a) 1 seconds b) 2 seconds c) 3 seconds d) 4 seconds e) none of these

Name	Mailbox

Name	Mailbox