

Practice Quiz 8
(no calculators allowed)

In the following problems you should use the Fourier transform and inverse transform integrals:

$$X(\omega) = \int_{-\infty}^{\infty} x(t)e^{-j\omega t} dt$$
$$x(t) = \frac{1}{2\pi} \int_{-\infty}^{\infty} X(\omega)e^{j\omega t} d\omega$$

Don't guess, manipulate the integrals!

1) If $x(t) \leftrightarrow X(\omega)$, then $\alpha x(t - \beta)$ will have Fourier transform

- a) $\alpha X(\omega)$ b) $\alpha X(\omega)e^{j\beta\omega}$ c) $\alpha X(\omega)e^{-j\beta\omega}$ d) none of these

2) If $x(t) \leftrightarrow X(\omega)$, then $\frac{d}{dt}x(t)$ will have Fourier transform

- a) $\frac{d}{d\omega}X(\omega)$ b) $j\omega X(\omega)$ c) $-j\omega X(\omega)$ d) none of these

3) If $x(t) \leftrightarrow X(\omega)$, then $tx(t)$ will have Fourier transform

- a) $\frac{d}{d\omega}X(\omega)$ b) $j\frac{d}{d\omega}X(\omega)$ c) $-j\frac{d}{d\omega}X(\omega)$ d) none of these

4) If $x(t) \leftrightarrow X(\omega)$, then $x(\alpha t)$ for $\alpha > 0$ will have Fourier transform

- a) $X\left(\frac{\omega}{\alpha}\right)$ b) $X(\alpha\omega)$ c) $\frac{1}{\alpha}X\left(\frac{\omega}{\alpha}\right)$ d) $\alpha X\left(\frac{\omega}{\alpha}\right)$ e) none of these

5) If $x(t) \leftrightarrow X(\omega)$, then $x(t)e^{-j\beta t}$ will have Fourier transform

- a) $X(\omega)e^{-j\beta t}$ b) $X(\omega + \beta)$ c) $X(\omega - \beta)$ d) none of these

6) If $x(t) = 2\delta(t+3)$, then $X(\omega)$ is

- a) $2e^{j3\omega}$ b) $2e^{j3\omega}u(t)$ c) $2e^{j3\omega}u(\omega)$ d) $2e^{-j3\omega}$ e) none of these

7) If $X(\omega) = 3\delta(\omega-2)$, then $x(t)$ is

- a) $3e^{j2t}$ b) $\frac{3}{2\pi}e^{j2t}$ c) $\frac{3}{2\pi}e^{j2t}u(t)$ d) $\frac{3}{2\pi}e^{-j2t}$ e) none of these

8) If $X(\omega) = \text{sinc}\left(\frac{\omega T}{\pi}\right)$, the first nulls (zero points) are at

- a) $\omega = \pm 1$ b) $\omega = \pm \frac{\pi}{T}$ c) $\omega = 0$ d) $\omega = \pm \frac{T}{\pi}$ e) none of these

9) If $x(t) = A\cos(2t)$, $X(\omega)$ will be nonzero

- a) for all ω b) at all $\omega = 2k$, k an integer c) $\omega = 2$ d) $\omega = \pm 2$

10) If we have the transfer function

$$H(s) = \frac{1}{(s+2)(s+20)}$$

the bandwidth of the system is

- a) 2 Hz b) 20 Hz c) 2 rad/sec d) 20 rad/sec e) none of these

Answers: 1) c 2) b 3) b 4) c 5) b 6) a 7) b 8) b 9) d 10) c