

ECE370 POWER & ENERGY SYSTEMS

Homework Set 3

3.1

- a) A coal-fired power plant employs a condenser that extracts 16 MJ for each kg of burned fuel. A neighboring oil-fired power plant employs a condenser that extracts 17 MJ for each kg of burned fuel. Calculate the mechanical energy of their turbines and their ideal efficiencies for:
- i) Petroleum with TEC = 40 MJ/kg ii) Coal with TEC = 24 MJ/kg
- b) Which plant will produce cheaper electricity if petroleum costs 75¢/kg and coal costs \$250 per tonne if both generating units have the same efficiency (equal η_{gen}).

3.2

- a) Calculate the mass of U^{235} required to produce an average of 750 MW of electricity annually, if the plant is 33 $\frac{1}{3}$ % efficient.
- b) Compare this with the equivalent mass of coal for a 25% efficient plant.
- c) Determine the ratio of volume of coal : volume of uranium.

Assume: $\rho_{Ur} = 21 \times 10^3 \text{ kg/m}^3$, $\rho_{coal} = 1 \frac{1}{4} \times 10^3 \text{ kg/m}^3$, $TEC_{coal} = 6.0 \text{ kWh/kg}$

3.3 A 250 kVA, 3600/240 V, single-phase transformer has the following test data:

	Voltage (V)	Current (A)	Power (W)
O/C Test	240	57.85	4985
S/C Test	187	69.45	4823

Use the approximate equivalent circuit to calculate:

- a) The voltage regulation and efficiency when the load takes 1100 A at 220 V and 0.6 lag pf. (NOTE: this is **not** rated load).
- b) The voltage regulation and efficiency at rated load conditions and 0.8 lag pf.
- 3.4 A hydroelectric development has two identical powerhouses each one has three penstocks and each penstock passes 200 m³/s of water with velocity 35 m/s when the average head behind the dam is 83.25 m. The generators operate at 0.9185 lag pf and the electricity is transmitted at 345 kV on three parallel transmission lines.
- a) Calculate the penstock efficiency.
- b) Assuming the coefficient of performance of the turbine is 0.6 and the generator efficiency is 95 $\frac{1}{4}$ %, what is the total generated real electrical power for the development?
- c) Calculate the magnitude of the current in the individual transmission lines.

3.5

You have a requirement for a three-phase transformer to handle 10 MVA with a voltage ratio of 2.4 kV: 12.471 kV kV. You are provided with three single-phase transformers each rated 15.75 MVA with voltage ratios of 12.471 kV : 37.4 kV.

- a) Draw a diagram showing how each transformer should be connected. Be sure to indicate the voltage applied to each winding. The tolerance on voltage is $\pm 0.25 \text{ kV}$.
- b) By what percentage is the bank underloaded or overloaded?